77

MOS FET Relays SOP 4-pin, General-purpose Type

# General-purpose MOS FET Relays in SOP 4-pin packages for a wide range of applications

• Load voltage: 200 V

RoHS Compliant





3. Package

G: SOP 4-pin

Note: The actual product is marked differently from the image shown here

## ■Application Examples

- · Semiconductor test equipment • Test & Measurement equipment
- Security equipment Industrial equipment
- Communication equipment
- Power circuit
- Amusement equipment

#### ■Package

(Unit: mm, Average)

SOP 4-pin



Note: The actual product is marked differently from the image shown here.

### ■Model Number Legend

G3VM-1 2 3 4

1. Load Voltage 2. Contact form 20:200 V 1:1a (SPST-NO)

4. Other informations

When specifications overlap, serial code is added in the recorded order.

Note: The model number legend for the G3VM-S5 is different from the above legend.

## **■**Ordering Information

				Continuous load current (peak value) *	Stick packa	ging	Tape packaging	
Package	Contact form	Terminals	Load voltage (peak value) *		Model	Minimum package quantity	Model	Minimum package quantity
	1a (SPST-NO)	Surface-mounting Terminals	200 V	50 mA	G3VM-201G	100 pcs.	G3VM-201G(TR)	2,500 pcs.
SOP4				200 mA	G3VM-201G1		G3VM-201G1(TR)	
50P4					G3VM-201G2		G3VM-201G2(TR)	
					G3VM-S5		G3VM-S5(TR)	

<sup>\*</sup> The AC peak and DC value are given for the load voltage and continuous load current.

Note: To order tape packaging for Relays with surface-mounting terminals, add "(TR)" to the end of the model number.

# ■Absolute Maximum Ratings (Ta = 25°C)

	Item	Symbol	G3VM-201G	G3VM-201G1	G3VM-201G2	G3VM-S5	Unit	Measurement conditions
	LED forward current	lF	5	0	30	50	mA	
Input	Repetitive peak LED forward current		1		Α	100 μs pulses, 100 pps		
lıb	LED forward current reduction rate	ΔIF/°C	-0	.5	-0.3	-0.5	mA/°C	Ta ≥ 25°C
	LED reverse voltage	VR			5		V	
	Connection temperature	TJ	125			°C		
	Load voltage (AC peak/DC)	Voff	200			V		
Ħ	Continuous load current (AC peak/DC)	lo	50 200		mA			
Output	ON current reduction rate	Δlo/°C	-0.5 -2		mA/°C	Ta ≥ 25°C		
0	Pulse ON current	lop	150		600		mA	t=100 ms, Duty=1/10
	Connection temperature	TJ	125			°C		
Dielectric strength between I/O (See note 1.)		V <sub>I</sub> -O	1500			Vrms	AC for 1 min	
An	Ambient operating temperature		-40 to +85			°C	With no icing or	
An	Ambient storage temperature		-55 to +125			°C	condensation	
Soldering temperature		-	260			°C	10 s	

Note: 1. The dielectric strength between the input and output was checked by applying voltage between all pins as a group on the LED side and all pins as a group on the light-receiving side.

## ■Electrical Characteristics (Ta = 25°C)

	Item	Symbol		G3VM-201G	G3VM-201G1	G3VM-201G2	G3VM-S5	Unit	Measurement conditions
	LED forward		Minimum	1.	.0	1.1	1.0		
	voltage	VF	Typical	1.1	15	1.27	1.15	٧	IF=10 mA
			Maximum	1.	.3	1.4	1.3		
	Reverse current	IR	Maximum	10		0		μА	VR=5 V
nbnt	Capacitance between terminals	Ст	Typical		30		pF	V=0, f=1 MHz	
	Trigger LED forward	let	Typical	1	0.4	1	1	mA	G3VM-201G : Io=50 mA
	current	IFI	Maximum	3	1	0.2	3	IIIA	G3VM-201G1/201G2/S5 : lo=200 mA
	Release LED	IEC	Minimum	0.	.1	-	0.1	mA	Ioff=100 μA
	forward current	110	Typical	-	-	0.001	-	III	100 μΑ
	Maximum	Ron	Typical	40		5			G3VM-201G/S5: IF=5 mA,
ŧ	resistance with output ON		Maximum	50		8		Ω	lo=Continuous load current ratings G3VM-201G1 : IF=2 mA, lo=200 mA G3VM-201G2 : IF=0.5 mA, lo=200 mA, t < 1s
Output	Current leakage		Typical	-		1	-		G3VM-201G : VoFF=160 V
ō	when the relay is open	İLEAK	Maximum	1		1,000		nA	G3VM-201G1/201G2/S5 : Voff=200 V
	Capacitance	COFF	Typical	15	9	0	100	pF	G3VM-201G : V=0, f=1 MHz, t < 10s
	between terminals	COFF	Maximum	20		-		þΓ	G3VM-201G1/201G2/S5 : V=0, f=1 MHz
	apacitance between I/ terminals	Cı-o	Typical		0	0.8		pF	f=1 MHz, Vs=0 V
Ins	sulation resistance	nce Bi-o Minimum		1000					Via FOO VDC Ball-609/
be	tween I/O terminals	HI-O	Typical	10 <sup>8</sup>				MΩ	Vi-o=500 VDC, RoH≤60%
Tu	rn-ON time	ton	Typical	I	3	3.5	0.6		G3VM-201G/S5 : IF=5 mA, RL=200 Ω,
Tu	IIII-ON IIIII	ION	Maximum	0.5	8	10	1.5	ms	VDD=20 V (See note 2.) G3VM-201G1 : IF=2 mA, RL=200 $\Omega$ ,
Total	rm-OFF time	tore	Typical	I	0.6	1	0.1	ins	VDD=20 V (See note 2.) G3VM-201G2 : IF=0.5 mA, RL=200 Ω,
lu	iiii-Oi i iiiile	IOFF	Maximum	0.2	3	5	1		VDD=20 V (See note 2.)

#### Note: 2. Turn-ON and Turn-OFF Times



# **■**Recommended Operating Conditions

For usage with high reliability, Recommended Operation Conditions is a measure that takes into account the derating of Absolute Maximum Ratings and Electrical Characteristics.

Each item on this list is an independent condition, so it is not simultaneously satisfy several conditions.


Item	Symbol		G3VM-201G	G3VM-201G1	G3VM-201G2	G3VM-S5	Unit	
Load voltage (AC peak/DC)	VDD	Maximum	160			200	٧	
0 " 150/ 1		Minimum 5 –		=	5			
Operating LED forward current	lF	Typical	7.5	2	0.5	7.5		
Current		Maximum	15		•	mA		
Continuous load current (AC peak/DC)	lo	Maximum	40	160		130		
Ambient operating	Ta	Minimum	-20					
temperature	l la	Maximum		6	65		°C	

# **■**Spacing and Insulation


Item	Minimum	Unit
Creepage distances	4.0	
Clearance distances	4.0	mm
Internal isolation thickness	0.1	

# ■Engineering Data LED forward current vs.


# Ambient temperature




 Continuous load current vs. On-state voltage




### Trigger LED forward current vs. Ambient temperature




#### Continuous load current vs. Ambient temperature




#### On-state resistance vs. Ambient temperature G3VM-201G




#### Turn ON, Turn OFF time vs. LED forward current G3VM-201G/S5




#### LED forward current vs. LED forward voltage



#### G3VM-201G1/201G2/S5




### G3VM-201G1/201G2




G3VM-201G\(\sigma\)/S5

## **■**Engineering Data


# Turn ON, Turn OFF time vs. Ambient temperature G3VM-201G/S5




#### G3VM-201G1/201G2



# Current leakage vs. Ambient temperature



#### Current leakage vs. Load voltage G3VM-201G2



# ■Appearance / Terminal Arrangement / Internal Connections

#### Appearance

#### SOP (Small Outline Package)

SOP 4-pin 4 3

OMPON logo

Pin 1 mark

OSE note 2.)

OTNO.

Note: 1. The actual product is marked differently from the image shown here.

Note: 2. "G3VM" does not appear in the model number on the Relay.

Note: 3. The indentation in the corner diagonally opposite from the pin 1 mark is from a pin on the mold.


# ●Terminal Arrangement/Internal Connections (Top View)



### **■Dimensions** (Unit: mm)

#### Surface-mounting Terminals

Weight: 0.1 g



### **Actual Mounting Pad Dimensions**

(Recommended Value, Top View)



Note: The actual product is marked differently from the image shown here.

## **■**Approved Standards

UL recognized

Approved Standards	Contact form	File No.		
UL (recognized)	1a (SPST-NO)	E80555		

#### **■**Safety Precautions

• Refer to the Common Precautions for All MOS FET Relays for precautions that apply to all MOS FET Relays.